

HCVR-SQA - SEQUENTIAL ACTIVATOR



DESCRIPTION

The HCVR-SQA is a sequential activator that is used to operate a fixed, condensed aerosol generator or canister for extinguishing fire in a confined space.

STANDARD FEATURES

- UL Listed and FM Approved
- Used to activate up to two FirePro® Xtnguish aerosol generators
- Includes a back box for surface mount
- Fault LED is illuminated to indicate trouble conditions

SPECIFICATIONS

Models	HCVR-SQA
Supply Voltage	24VDC
Average Current Consumption	1mA
Maximum Output Current	1A @ 24VDC
Material	Mild steel
Dimensions	3.58"W x 3.58"H x 1.61"D

COMPATIBILITY LIST

CANISTER TYPE	BOX TYPE
HOCHIKI AMERICA	
FNX-100S	FNX-1200
FNX-200S	FNX-2000
FNX-500S	FNX-3000
	FNX-5700
FIREPRO	
FP-100S	FP-1200
FP-200S	FP-2000
FP-500S	FP-3000
	FP-5700

PRODUCT LISTINGS

SIGNALING



California State
Fire Marshal
7300-0410:0207

Specifications subject to change without notice.

Continued on back.

Hochiki America Corporation
7051 Village Drive, Suite 100, Buena Park, CA 90621-2268
Phone: 714/522-2246 Fax: 714/522-2268
Technical Support: 800-845-6692 or technicalsupport@hochiki.com



Find latest revision at www.hochiki.com

F0167 09/2015

HCVR-SQA - SEQUENTIAL ACTIVATOR

WIRING DIAGRAMS

